

# DIGIEVER Network Camera Compatibility List

The list is applied for DIGIEVER NVR firmware 76 version or later

Update: Jan. 2024

- DIGIEVER NVR supports the camera feature
- Ⓟ 360° Panoramic
- ◆ Camera takes more than 1CH, needed to be added via video sever method
- 1. Audio Detection
- IVA Event 2. Advanced Motion Detection
- No.: 3. Human Detection
- 4. Cross Line Detection
- \* Camera does not support the feature
- Ⓢ NVR support camera hardware dewarp
- 5. Intrusion Detection
- 6. Loitering Detection
- 7. Foreign Object Detection
- 8. Missing Object Detection
- Blank means the feature is NOT supported or verified by DIGIEVER
- Ⓢ NVR support camera software dewarp
- 9. People Counting Threshold Alarm
- 10. Temperature Detection
- 11. Camera Tampering Detection
- 12. Object Status Change

Supported in the NVR latest version  
 Copyright © DIGIEVER Corporation All Rights Reserved \* Please contact DIGIEVER sales for updated information

Brand	Camera Model	Compression				Zoom Control			Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	Advanced Right-Click Menu	Camera Firmware/ Note
		MJPEG	MPEG -4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom								
TOA	(DIGIEVER NVR supports TOA cameras with audio format: G711, AAC)															
	TOA N-C3300F2		*	●	*	*	*	●	●	*	●	●				1.1.2.0.31 1.6.1.4.124
	TOA N-C5120-3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●		*	Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5130	●	*	●	●	*	*	●	●	●	● (AAC)	●		Trigger DO x 1		
	TOA N-C5130-3	●	*	●	●	*	*	●	●	●	● (AAC)	●		Trigger DO x 1		
	TOA N-C5150	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●		Trigger DO x 1	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5150-3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●		Trigger DO x 1	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5220-3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●		*	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5250R3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●		Trigger DO x 1	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5230R3	●	*	●	●	*	*	●	●	●	● (AAC)	●		Trigger DO x 1		
	TOA N-C5430R3	●	*	●	●	*	*	●	●	●	● (AAC)	●		Trigger DO x 1		
	TOA N-C5830R3	●	*	●	●	*	*	●	●	●	● (AAC)	●		Trigger DO x 1		
	TOA N-C5300-M	●	*	●	●	*	*	●	● (ONVIF)	*	*	●			1.9.0.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5305-M	●	*	●	●	*	*	●	● (ONVIF)	*	*	●			1.9.0.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5300F3-M	●	*	●	●	*	*	●	● (ONVIF)	*	*	●			1.9.0.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5305F3-M	●	*	●	●	*	*	●	● (ONVIF)	*	*	●			1.9.0.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5420-3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●		*	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5430R3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)	●	●		Trigger DO x 1	1.9.1.4.21 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	

Brand	Camera Model	Compression				Zoom Control				Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	Advanced Right-Click Menu	Camera Firmware/ Note
		MJPEG	MPEG -4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom									
	TOA N-C5450R3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●			Trigger DO x 1	1.4.1.4.161 1.6.1.4.124 1.6.2.4.131 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5500	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●			Trigger DO x 1	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5700	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●			Trigger DO x 1	1.4.1.4.161 1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5820-3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)		●			*	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5830R3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)	●	●			Trigger DO x 1	1.9.1.4.21 Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
	TOA N-C5850R3	●	*	●	●	*	*	●	● (ONVIF)	● (ONVIF)	●	●			Trigger DO x 1	1.6.1.4.124 Parameter Mode: Mode1: Stream1:H.264, Stream2: H.264 Mode2: Stream1: MJPEG, Stream2: H.264	
<b>(DIGIEVER NVR supports TOA cameras with ONVIF)</b>																	
	TOA N-C3120-3		*	●	*	*	*	●	●	*	*	*					1.3.0.534.284
	TOA N-C5220-3	*	*	●		*	*	*	●	*	*						1.0.0.1.347 *Support stream1 only due to camera performance limitation.
<b>(DIGIEVER NVR supports TOA video server)</b>																	
	TOA N-V5020-1	●	*	●	●	*	*	●	●	●	●	*			Trigger DO x 2	1.7.1.4.84	
	TOA V-V5050P1	●	*	●	●	*	*	●	●	●	●	*			Trigger DO x 2	1.7.1.4.84	
<b>(DIGIEVER NVR supports TOA IP Horn Speaker with ONVIF)</b>																	
<b>TOA Speaker camera: need to chose ONVIF at "Brand Option" when adding the camera to NVR, and the Brand Name will change to TOA automatically afterin adding the speaker</b>																	
	TOA IP-A1AF	*	*	*	*	*	*	*	*	*	*	●			Audio Pattern 1~10	2.2.0	
	TOA IP-A1PC238	*	*	*	*	*	*	*	*	*	*	●			Audio Pattern 1~10	2.2.0	
	TOA IP-A1SC15	*	*	*	*	*	*	*	*	*	*	●			Audio Pattern 1~10	2.2.0	
<b>(DIGIEVER NVR supports TOA Gateway Unit)</b>																	
	TOA IP-A1PG	*	*	*	*	*	*	*	*	*	*	*			Audio Channel 1~5 Pattern List 1~20	2.2.0	

**Note:**

1. More models are under integration and will be released soon.
2. Two-way audio: ACTi, AXIS, Brickcom, Canon, Hi-Sharp, Honeywell, Levelone, Milesight, Risk Captur, SONY, TOA (5-generation camera), VIVOTEK (LAN), WatchNet
3. Edge recording: ACTi, AXIS (H.264 only), Brickcom, Dynacolor, Honeywell, Hunt, SONY(H.264 only), VIVOTEK, WatchNet
4. VB Search supports Canon cameras listed in the compatible list except VB-C series.
5. Local liveview supports ImmerVersion engine codec of H.264 and MJPEG only.
6. For camera added via ONVIF protocol, please follow below steps to set up camera event (like motion detection, digital input, tampering detection) on DIGIEVER:
  - (1) On DIGIEVER NVR: Enable camera event on event and action management page.
  - (2) On camera webpage: Enable camera event on camera setting page
7. NVR supports H.264 and H.265 through ONVIF. For MJPEG format, please use Generic\_MJPEG to add the camera.
8. NVR supports Honeywell IVA through ONVIF (by Model): Motion Detection, Advanced Motion Detection, Tampering Detection, Intrusion Detection, Loitering Detection, People Counting Threshold Notice
9. Cameras are not supported in Camera Digital Output in the Event & Action Management : Canon and TOA

Copyright © DIGIEVER Corporation All Rights Reserved

✘ **Camera IVA event support list:**

1. **Audio detection:** ACTi, AXIS
2. **Advanced motion detection:** AXIS, Hanwha, Hitron, Milesight, WatchNet
3. **Human detection:** ACTi, AXIS, Hanwha, Levelone, Milesight, WatchNet
4. **Cross line detection:** AXIS, Brickcom, Canon, Hanwha, Hikvision, Honeywell, Levelone, Milesight, Risk Captur, WatchNet  
(Note: If camera resolution is higher than 4K, local display doesn't support tripwire.)
5. **Intrusion detection:** ACTi, AXIS, Brickcom (specific version), Hitron, Honeywell, Risk Captur
6. **Loitering detection:** AXIS, Brickcom (specific version), Honeywell, Milesight, Risk Captur, WatchNet
7. **Foreign object detection:** AXIS, Brickcom (specific version), Hitron
8. **Missing object detection:** ACTi, AXIS, Brickcom (specific version), Hitron
9. **People counting threshold alarm:** AXIS, Hanwha, Honeywell, Milesight, Risk Captur, VIVOTEK, WatchNet
10. **Temperature detection:** EOC, FLIR, Honeywell, Mobotix
11. **Camera tampering detection:** Axis, EOC, Hitron, Honeywell, Milesight, WatchNet
12. **Object Status Change:** Axis, Dahua