

DIGIEVER Network Camera Compatibility List

The list is applied for DIGIEVER NVR firmware 76 version or later

Update: Jan. 2024

- DIGIEVER NVR supports the camera feature
- * Camera does not support the feature
- Ⓟ 360° Panoramic
- Ⓢ NVR support camera hardware dewarp
- Ⓣ NVR support camera software dewarp
- Blank means the feature is NOT supported or verified by DIGIEVER
- ◆ Camera takes more than 1CH, needed to be added via video sever method
- 1. Audio Detection
- 2. Advanced Motion Detection
- 3. Human Detection
- 4. Cross Line Detection
- 5. Intrusion Detection
- 6. Loitering Detection
- 7. Foreign Object Detection
- 8. Missing Object Detection
- 9. People Counting Threshold Alarm
- 10. Temperature Detection
- 11. Camera Tampering Detection
- 12. Object Status Change

Supported in the NVR latest version
 Copyright © DIGIEVER Corporation All Rights Reserved * Please contact DIGIEVER sales for updated information

Brand	Camera Model	Compression				Zoom Control			Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	Advanced Right-Click Menu	Camera Firmware/ Note
		MJPEG	MPEG -4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom								
D-Link (DIGIEVER NVR supports D-Link cameras with audio format: G711)																
D-Link	DCS-3122	●	●	●	*	*	*	●	●		●					
D-Link	DCS-3710B1	●	●	*	*	*	*	●	●		●					
D-Link	DCS-3716	●	●	●	*	*	*	●	●	*	●					
D-Link	DCS-4602EV		*	●	*	*	*	●	●	*	●					
D-Link	DCS-4621	●	●	●	*	*	*	●	●		●				VE1.0.18.2	
D-Link	DCS-4701E	●	*	●	*	*	*	●	●	*	*				1.04.02	
D-Link	DCS-4710	●	●	●	*	*	*	●	●		●				VE1.0.16.10	
D-Link	DCS-5222LB1	●		●	*	*	*	●	●	*	●					
D-Link	DCS-6112			●	*	*	*	●	●	●	●					
D-Link	DCS-6113			●	*	*	*	●	●	●	●					
D-Link	DCS-6314	●	*	●	*	*	*	●	●	*	●					
D-Link	DCS-6511	●		●	*	*	*	●	●	*	●					
D-Link	DCS-6513	●	*	●	*	*	*	●	●	*	●					
D-Link	DCS-7413	●		●	*	*	*	●	●	*	●					
D-Link	DCS-7513	●		●	*	*	*	●	●	*	●					
(DIGIEVER NVR supports D-Link cameras with ONVIF)																
D-Link	DCS-2132L			●	*	*	*	●	●		●					
D-Link	DCS-2332L			●	*	*	*	●	●	*	●					
D-Link	DCS-6010L			●	*	*	*	●	●		●					
D-Link	DCS-6210			●	*	*	*	●	●	*	●					
D-Link	DCS-7010L			●	*	*	*	●	●	*	●					
D-Link	DCS-7110			●	*	*	*	●	●	*	*					
D-Link	DCS-933L		*	●	*	*	*	●	●	*	●					
(DIGIEVER NVR supports D-Link cameras with Generic RTSP/ Generic MJPEG method)																
URL		Generic MJPEG														
D-Link	DCS-6113V	http://<servername>:<serverport>/video/mjpeg.cgi														
D-Link	DCS-7110	http://<servername>:<serverport>/video/mjpeg.cgi														

- Note:**
- More models are under integration and will be released soon.
 - Two-way audio: ACTi, AXIS, Brickcom, Canon, Hi-Sharp, Honeywell, Levelone, Milesight, Risk Captur, SONY, TOA (5-generation camera), VIVOTEK (LAN), WatchNet
 - Edge recording: ACTi, AXIS (H.264 only), Brickcom, Dynacolor, Honeywell, Hunt, SONY(H.264 only), VIVOTEK, WatchNet
 - VB Search supports Canon cameras listed in the compatible list except VB-C series.
 - Local liveview supports ImmerVersion engine codec of H.264 and MJPEG only.
 - For camera added via ONVIF protocol, please follow below steps to set up camera event (like motion detection, digital input, tampering detection) on DIGIEVER:
 - On DIGIEVER NVR: Enable camera event on event and action management page.
 - On camera webpage: Enable camera event on camera setting page
 - NVR supports H.264 and H.265 through ONVIF. For MJPEG format, please use Generic_MJPEG to add the camera.
 - NVR supports Honeywell IVA through ONVIF (by Model): Motion Detection, Advanced Motion Detection, Tampering Detection, Intrusion Detection, Loitering Detection, People Counting Threshold Notice
 - Cameras are not supported in Camera Digital Output in the Event & Action Management : Canon and TOA

Copyright © DIGIEVER Corporation All Rights Reserved

Brand	Camera Model	Compression				Zoom Control			Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	Advanced Right-Click Menu	Camera Firmware/ Note
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom								

※ Camera IVA event support list:

1. **Audio detection:** ACTi, AXIS
2. **Advanced motion detection:** AXIS, Hanwha, Hitron, Milesight, WatchNet
3. **Human detection:** ACTi, AXIS, Hanwha, Levelone, Milesight, WatchNet
4. **Cross line detection:** AXIS, Brickcom, Canon, Hanwha, Hikvision, Honeywell, Levelone, Milesight, Risk Captur, WatchNet
(Note: If camera resolution is higher than 4K, local display doesn't support tripwire.)
5. **Intrusion detection:** ACTi, AXIS, Brickcom (specific version), Hitron, Honeywell, Risk Captur
6. **Loitering detection:** AXIS, Brickcom (specific version), Honeywell, Milesight, Risk Captur, WatchNet
7. **Foreign object detection:** AXIS, Brickcom (specific version), Hitron
8. **Missing object detection:** ACTi, AXIS, Brickcom (specific version), Hitron
9. **People counting threshold alarm:** AXIS, Hanwha, Honeywell, Milesight, Risk Captur, VIVOTEK, WatchNet
10. **Temperature detection:** EOC, FLIR, Honeywell, Mobotix
11. **Camera tampering detection:** Axis, EOC, Hitron, Honeywell, Milesight, WatchNet
12. **Object Status Change:** Axis, Dahua